

# FALKON

## Horizontal Windlass

1700 W / 2000 W



Standard Type

### Main Features

- Marine anodised aluminium body
- Independent gypsy and drum operation
- Manual chain release
- Manual override
- IP67 motor cover

### Standard Equipment

- Dual direction solenoid pack
- Handle
- Gypsy for chain
- QR code card for Instruction Manual

# FALKON Horizontal Windlass

1700 W / 2000 W

Construction		Anodised Aluminium		
Motor Size		1700 W		2000 W
Power Supply (V)		12	24	24
Maximum Pull (kg)		1700	1800	2640
Working Load (kg)		215	225	330
Amps at Working Load (A)		210	100	110
Line Speed at Working Load (m/min)		14	15	19
Max. Line Speed (m/min)		33	33	33
Net Weight (kg)		55	55	57

  

FALKON	Type		Code	Code	Code
	Standard <i>(Drum port &amp; Gypsy starboard)</i>	10 mm, ISO 4565 / 3/8" HT	220293	418511	636670
		10 mm, DIN 766	600063	600067	*
		12 mm, ISO 4565 / 13mm, DIN 766	404732	404733	636606
		7/16" HT	*	*	636671
		1/2" HT	600446	600471	636672
	Gypsy port & Gypsy starboard	600432	600448	636673	

For additional options on compatible gypsies, please check below.  
 If you are interested in an alternative configuration not listed above or any other special product, please contact our team. Product codes with \* are available upon request.

### Dimensions (mm)

Model	A	D	F	L	M	N
1700 W	345	Ø104	500	147	240	235

  

Model	Type	A	D	F	L	M	N
2000 W	Standard	340	Ø104	500	147	240	235
	Gypsy port & Gypsy starboard	345	-	510	147/140	238	292

### Combine with

#### Compatible Gypsies

Code	Gypsy Size
631132	10 mm, DIN 766 - 3/8" BBB
636570	10 mm, ISO 4565 - 3/8" HT
636572	12-13mm, DIN 766
631050	13mm, DIN 764
631059	14mm
631033	1/2" BBB
631036	1/2" G40
631124	3/8" G40
631129	5/16" HT
636571	7/16" HT

#### Optional Accessories

- Foot Switch
- Control Switch
- Circuit Breaker
- Chain Counter
- Hand Held Control
- Radio Control
- Chain Stopper

#### KEEP YOUR LOFRANS' AS GOOD AS NEW!

#### Maintenance Kit for FALKON

Code I 72051

Please refer to Deck Hardware & Accessories section for control and installation products (pages 76-89).